

Link do produktu: <https://vipelektrogadzet.pl/plyta-msi-mag-b850-tomahawk-max-wifi-ii-amd-b850ddr5sata3m2usb32wifibtpcie50am5atx-p-289928.html>

BRAK
ZDJĘCIA



Płyta MSI MAG B850 TOMAHAWK MAX WIFI II /AMD B850/DDR5/SATA3/M.2/US B3.2/WiFi/BT/PCIe5.0/AM5/ATX

Cena	1 124,17 zł
Numer katalogowy	INC-PGMIA5M510F0
Kod producenta	MAG B850 TOMAHAWK MAX WIFI II
Kod EAN	4711377424011

Opis produktu

Parametry

- **Gniazdo procesora:** Socket AM5
- **Obsługiwane typy procesorów:** AMD Ryzen™ (AM5)
- **Uwagi do procesora:** Supports AMD Ryzen 9000/ 8000/ 7000 Series Desktop Processors
- **Format płyty:** ATX
- **BIOS:**
- **Chipset płyty głównej:** AMD B850
- **Ilość złącz pamięci DDR5:** 4
- **Maksymalna wielkość pamięci:** 256 GB
- **Tryb pracy pamięci RAM:** Dual Channel
- **Standard pamięci:** DDR5-8400 (OC), DDR5-8200 (OC), DDR5-8000 (OC), DDR5-7900 (OC), DDR5-7800 (OC), DDR5-7600 (OC), DDR5-7400 (OC), DDR5-7200 (OC), DDR5-7000 (OC), DDR5-6800 (OC), DDR5-6600 (OC), DDR5-6400 (OC), DDR5-6200 (OC), DDR5-6000 (OC), DDR5-5800 (OC), DDR5-5600 (OC), DDR5-5600, DDR5-5400, DDR5-5200, DDR5-5000, DDR5-4800
- **Uwagi do pamięci RAM:** Ryzen 9000 Series Processors max. overclocking frequency:, - 1DPC 1R Max speed up to 8400+ MT/s, - 1DPC 2R Max speed up to 6400+ MT/s, - 2DPC 1R Max speed up to 6400+ MT/s, - 2DPC 2R Max speed up to 6400+ MT/s, Supports AMD POR Speed and JEDEC Speed, Supports Memory Overclocking and AMD EXPO, Supports Non-ECC, Un-buffered memory, Supports CUDIMM, Clock Driver bypass mode only
- **Zintegrowany kontroler SATA:** Chipset+CPU: 4x SATA III 6Gb/s + 4x M.2 - RAID 0,1,10
- **Uwagi do kontrolera SATA:** - M.2_1 Source (From CPU) supports up to PCIe 5.0 x4,, supports 22110/2280 devices, - M.2_2 Source (From CPU) supports up to PCIe 5.0 x4,, supports 2280/2260 devices, - M.2_3 Source (From Chipset) supports up to PCIe 4.0 x2,, - M.2_4 Source (From Chipset) supports up to PCIe 4.0 x4,, M2_1 slot:, - Supports up to PCIe 5.0 x4 (For Ryzen™ 9000/ 7000 Series processors), - Supports up to PCIe 4.0 x4 (For Ryzen™ 8000 Series processors), M2_2 slot:, - Supports up to PCIe 4.0 x4 (For Ryzen™ 8700/8600/8400 Series processors), - Supports up to PCIe 4.0 x2 (For Ryzen™ 8500/ 8300 Series processors), PCI_E3 slot will run at x2 speed when installing device in the M2_3 slot., You can switch PCI_E3 slot to x4 in the BIOS, but this will disable the, M2_3 slot.
- **Wbudowana karta graficzna:** Brak lub AMD Radeon™ Graphics (zależy od procesora)
- **Gniazda karty graficznej:** HDMI
- **Uwagi do karty graficznej:** Support HDMI™ 2.1 FRL, maximum resolution of 8K 60Hz, Available only on processors featuring integrated graphics, Graphics specifications may vary depending on the CPU installed
- **Zintegrowana karta dźwiękowa:** Realtek® ALC4080 7.1-Channel USB High Performance Audio CODEC
- **Gniazda karty dźwiękowej:** 2x Audio Jack, Wyjście optyczne S/PDIF, Wewnętrzne gniazdo audio przedniego panelu
- **Uwagi do karty dźwiękowej:**
- **Złącza PCI Express x16:** 3
- **Uwagi do złącz PCI:** - PCI_E1 Gen PCIe 5.0 supports up to x16 (From CPU), - PCI_E2 Gen PCIe 3.0 supports up to x1 (From Chipset), - PCI_E3 Gen PCIe 4.0 supports up to x4 (From Chipset), PCI_E1 slot:, - Supports PCIe 5.0 x16 (For Ryzen™ 9000/ 7000 Series processors), - Supports PCIe 4.0 x8 (For Ryzen™ 8700/ 8600/ 8400 Series processors), - Supports PCIe 4.0 x4 (For Ryzen™ 8500/ 8300 Series processor)
- **Port LAN:** 1x 5 Gigabit LAN Realtek® 8126VB
- **Uwagi do karty sieciowej:**
- **Maksymalna ilość portów USB 2.0:** 8
- **Maksymalna ilość portów USB 3.x:** 11

-
- **Porty USB na panelu tylnym:** 4x USB 2.0 + 1x USB 3.0 + 2x USB 3.1 + 3x USB 3.1 Type-C
 - **Gniazda USB na płycie głównej:** 2x USB 2.0 (4 porty) + 2x USB 3.0 (4 porty) + 1x USB 3.2 Type-C (1 port)
 - **Port Wi-Fi:** IEEE 802.11a/b/g/n/ac/ax/be
 - **Port Bluetooth:** Bluetooth V5.4
 - **Uwagi do WiFi / BT:** Wi-Fi 7 Solution, The Wireless module is pre-installed in the M.2 (Key-E) slot, Supports MU-MIMO TX/RX, 2.4GHz/ 5GHz/ 6GHz (320MHz) up to 5.8Gbps, Supports Bluetooth 5.4, MLO, 4KQAM, 6GHz band support may depend on every country's regulations and Wi-Fi 7, will be ready in Windows 11 version 24H2, The Bluetooth version may be updated, please refer to the Wi-Fi chipset, vendor's website for details, Bluetooth 5.4 will be ready in Windows 11 version 24H2
 - **Port PS/2:** Brak
 - **Port szeregowy (COM):** Brak
 - **Port równoległy (LPT):** Brak
 - **Inne porty i gniazda:** CPU Fan, Combo Fan (Pump_Sys Fan), 6x System Fan, EZ Conn-header (JAF_1), 2x Front Panel, Chassis Intrusion (JCI), Front Audio, 3x Addressable V2 RGB LED connector, RGB LED connector, Gniazdo modułu TPM, 2x Direct OC Jumper (JBCLK), 4x EZ Debug LED, Clear CMOS button(s), Flash BIOS Button, 2x Antenna Ports
 - **Gniazdo zasilania:** ATX (24-pin) + 2x ATX12V (8-pin) + PCIe (8-pin)
 - **Wymiary [S x W] (mm):** 243,84 x 304,8
 - **Opakowanie:** BOX
 - **Wyposażenie dodatkowe:** SATA Cable, Cable Sticker, EZ Wi-Fi antenna, Quick Installation Guide, European Union Regulatory Notice, EZ M.2 Clip II, EZ M.2 Clip II Remover, 1 to 3 EZ Conn-Cable (V2)
 - **Zawiera baterię / akumulator:** Tak
 - **Informacje dodatkowe:** Support for Windows 11 64-bit
 - **Gwarancja producenta [mies.]:** 36